

**SETTING UP YOUR INTERNET**

There are two ways to set up your Internet connection. You can use the Web-based Internet Connection Setup Wizard or you can manually configure the connection.

Please make sure you have your ISP's connection settings first if you choose manual setup.

**INTERNET CONNECTION WIZARD**

You can use this wizard for assistance and quick connection of your new D-Link Router to the Internet. You will be presented with step-by-step instructions in order to get your Internet connection up and running. Click the button below to begin.

[Setup Wizard](#)

**Note:** Before launching the wizard, please ensure you have correctly followed the steps outlined in the Quick Installation Guide included with the router.

**Helpful Hints...**

First time users are recommended to run the **Setup Wizard**. Click the **Setup Wizard** button and you will be guided step by step through the process of setting up your ADSL connection.

If you consider yourself an advanced user or have configured a router before, click **Setup->Internet Setup** to input all the settings manually.

[More...](#)
**1 > STEP 2: SET TIME AND DATE > 3 > 4 > 5**

The Time Configuration option allows you to configure, update, and maintain the correct time on the internal system clock. From this section you can set the time zone that you are in and set the NTP (Network Time Protocol) Server. Daylight Saving can also be configured to automatically adjust the time when needed.

**SYSTEM TIME**

**System time:** Sun Jan 1 0:2:32 2012

**Time Zone:** (GMT-00:00) Casablanca, Monrovia

**DayLight:** LocalTIME

**Mode:** Copy Computer time

[Back](#)
[Next](#)
[Cancel](#)

**STEP 1: CHANGE DEVICE LOGIN PASSWORD** > 2 > 3 > 4 > 5

To help secure your network, D-Link recommends that you should choose a new password. If you do not wish to choose a new password now, just click "Skip" to continue. Click "Next" to proceed to next step.

Current Password :

New Password :

Confirm Password :

**1 — 2 — STEP 3: SETUP INTERNET CONNECTION — 4 — 5**

Please select your WAN Physical Type.

WAN Physical Type : DSL WAN ▼

**ISP**

Please select your Country and ISP (Internet Service Provider) from the list below. If your Country or ISP is not in the list, please select "Others".

Country : Syria ▼

Internet Service Provider : scs-net ▼

Protocol : PPPoE ▼

Connection Type : LLC ▼

VPI : 8 (0-255)

VCI : 35 (32-65535)

**PPPoE**

Please enter your Username and Password as provided by your ISP (Internet Service Provider). Please enter the information exactly as shown taking note of upper and lower cases. Click "Next" to continue.

Username : username @ scs-net.sy

Password : \*\*\*\*\*

Confirm Password : \*\*\*\*\*




## 1 — 2 — 3 — STEP 4: CONFIGURE WIRELESS NETWORK — 5

Your wireless network is enabled by default. You can simply uncheck it to disable it and click "Next" to skip configuration of wireless network.

☒ **Enable Your Wireless Network**

Your wireless network needs a name so it can be easily recognized by wireless clients. For security purposes, it is highly recommended to change the pre-configured network name.


**Wireless Network Name (SSID) :**  (1~32 characters) 

Select "Visible" to publish your wireless network and SSID can be found by wireless clients, or select "Invisible" to hide your wireless network so that users need to manually enter SSID in order to connect to your wireless network.

**Visibility Status :** ☒ Visible ☐ Invisible

In order to protect your network from hackers and unauthorized users, it is highly recommended you choose one of the following wireless network security settings.

**Security Level :**


☐ None ☐ WEP ☐ WPA-PSK ☒ WPA2-PSK 

**Security Mode:** WPA-PSK

Select this option if your wireless adapters support WPA-PSK.

Now, please enter your wireless security key.

**WPA2 Pre-Shared Key :**



(8~63 Characters, such as a~z, A~Z, or 0~9, i.e. '%Fortress123&')

**Note:** You will need to enter the same key here into your wireless clients in order to enable proper wireless connection.

[Back](#)[Next](#)[Cancel](#)

# 1 — 2 — 3 — 4 — STEP 5: COMPLETED AND APPLY

Setup complete. Click "Back" to review or modify settings. Click "Apply" to apply current settings.

If your Internet connection does not work after apply, you can try the Setup Wizard again with alternative settings or use Manual Setup instead if you have your Internet connection details as provided by your ISP.

## SETUP SUMMARY

Below is a detailed summary of your settings. Please print this page out, or write the information on a piece of paper, so you can configure the correct settings on your wireless client adapters.

<b>Modem Password :</b>	admin1
<b>Time Settings :</b>	Copy from Computer
<b>WAN Physical Type :</b>	DSL WAN
<b>VPI / VCI :</b>	8/35
<b>Protocol :</b>	PPPoE
<b>Connection Type :</b>	LLC
<b>Username :</b>	qseemoh@tarassul.sy
<b>Password :</b>	
<b>Wireless Network :</b>	Enabled
<b>Wireless Network Name (SSID) :</b>	Qusai
<b>Visibility Status :</b>	Invisible
<b>Encryption :</b>	WPA2-PSK/AES (also known as WPA2 Personal)
<b>Pre-Shared Key :</b>	p@ssw0rd1994qusai

Back

Apply

Cancel